

## Einstellwerte für gedrehte Kontakte Settings for closed turned contacts

Werkzeuge / Tools  
97 52 63 A / 97 52 63 DG A

Hinweis: Das Einstellmaß und die Locator-Position der Crimpzange sind entsprechend dem Leiterquerschnitt anzupassen. Zur Ermittlung der hier aufgeführten Crimpeinstellungen wurde ein handelsübliches, feindrähtiges Litzenkabel verwendet. Die ermittelten Werte sind lediglich Richtgrößen und ohne Gewähr. Die Crimpeinstellungen sind vom Anwender mit der jeweils eingesetzten Litze konkret zu prüfen.

*Note: The crimping depth and the locator position on the crimping tool must be adjusted to match the conductor cross-section. A standard, fine-stranded cable was used to determine the crimping settings listed here. The values given are for guidance only and are provided without warranty. The user must verify the crimping settings specifically for the stranded cable being used.*

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm <sup>2</sup> ]	Locator- position
Phoenix Contact	97 59 63 PC3	HC-11P2000	1623428	-	-	0,65	0,08	1
Phoenix Contact	97 59 63 PC3	HC-11P2000	1623428	-	-	0,69	0,14	1
Phoenix Contact	97 59 63 PC3	HC-11P2000	1623428	-	-	0,69	0,22	1
Phoenix Contact	97 59 63 PC3	HC-11S2000	1623429	-	-	0,65	0,08	2
Phoenix Contact	97 59 63 PC3	HC-11S2000	1623429	-	-	0,67	0,14	2
Phoenix Contact	97 59 63 PC3	HC-11S2000	1623429	-	-	0,69	0,22	2
Phoenix Contact	97 59 63 PC3	HC-12P2000	1623430	-	-	0,63	0,14	1
Phoenix Contact	97 59 63 PC3	HC-12P2000	1623430	-	-	0,65	0,22	1
Phoenix Contact	97 59 63 PC3	HC-12P2000	1623430	-	-	0,67	0,38	1
Phoenix Contact	97 59 63 PC3	HC-12P2000	1623430	-	-	0,69	0,56	1
Phoenix Contact	97 59 63 PC3	HC-12S2000	1623431	-	-	0,63	0,14	2
Phoenix Contact	97 59 63 PC3	HC-12S2000	1623431	-	-	0,65	0,22	2
Phoenix Contact	97 59 63 PC3	HC-12S2000	1623431	-	-	0,67	0,38	2
Phoenix Contact	97 59 63 PC3	HC-12S2000	1623431	-	-	0,69	0,56	2
Phoenix Contact	97 59 63 PC3	HC-1KP2000	1623432	-	-	0,75	0,50	1
Phoenix Contact	97 59 63 PC3	HC-1KP2000	1623432	-	-	0,80	0,75	1
Phoenix Contact	97 59 63 PC3	HC-1KP2000	1623432	-	-	1,00	1,00	1
Phoenix Contact	97 59 63 PC3	HC-1KS2000	1623433	-	-	0,75	0,50	2
Phoenix Contact	97 59 63 PC3	HC-1KS2000	1623433	-	-	0,80	0,75	2
Phoenix Contact	97 59 63 PC3	HC-1KS2000	1623433	-	-	1,00	1,00	2
Phoenix Contact	97 59 63 PC3	RC-11P2000	1596770	-	-	0,65	0,08	1
Phoenix Contact	97 59 63 PC3	RC-11P2000	1596770	-	-	0,67	0,14	1
Phoenix Contact	97 59 63 PC3	RC-11P2000	1596770	-	-	0,69	0,22	1
Phoenix Contact	97 59 63 PC3	RC-11S2000	1596772	-	-	0,65	0,08	2
Phoenix Contact	97 59 63 PC3	RC-11S2000	1596772	-	-	0,67	0,14	2
Phoenix Contact	97 59 63 PC3	RC-11S2000	1596772	-	-	0,69	0,22	2
Phoenix Contact	97 59 63 PC3	RC-12P2000	1597862	-	-	0,63	0,14	1
Phoenix Contact	97 59 63 PC3	RC-12P2000	1597862	-	-	0,65	0,22	1
Phoenix Contact	97 59 63 PC3	RC-12P2000	1597862	-	-	0,67	0,38	1
Phoenix Contact	97 59 63 PC3	RC-12P2000	1597862	-	-	0,69	0,56	1
Phoenix Contact	97 59 63 PC3	RC-12S2000	1599600	-	-	0,63	0,14	2
Phoenix Contact	97 59 63 PC3	RC-12S2000	1599600	-	-	0,65	0,22	2
Phoenix Contact	97 59 63 PC3	RC-12S2000	1599600	-	-	0,67	0,38	2
Phoenix Contact	97 59 63 PC3	RC-12S2000	1599600	-	-	0,69	0,56	2
Phoenix Contact	97 59 63 PC3	RC-1KP2000	1602996	-	-	0,75	0,50	1
Phoenix Contact	97 59 63 PC3	RC-1KP2000	1602996	-	-	0,80	0,75	1
Phoenix Contact	97 59 63 PC3	RC-1KP2000	1602996	-	-	1,00	1,00	1
Phoenix Contact	97 59 63 PC3	RC-1KS2000	1602998	-	-	0,75	0,50	2
Phoenix Contact	97 59 63 PC3	RC-1KS2000	1602998	-	-	0,80	0,75	2
Phoenix Contact	97 59 63 PC3	RC-1KS2000	1602998	-	-	1,00	1,00	2
Phoenix Contact	97 59 63 PC3	RC-20KP0,08-0,56	1240882	-	-	0,44	0,08	1
Phoenix Contact	97 59 63 PC3	RC-20KP0,08-0,56	1240882	-	-	0,49	0,14	1
Phoenix Contact	97 59 63 PC3	RC-20KP0,08-0,56	1240882	-	-	0,59	0,25	1
Phoenix Contact	97 59 63 PC3	RC-20KP0,08-0,56	1240882	-	-	0,67	0,34	1
Phoenix Contact	97 59 63 PC3	RC-20KP0,08-0,56	1240882	-	-	0,72	0,50	1
Phoenix Contact	97 59 63 PC3	RC-20KS0,08-0,56	1241093	-	-	0,44	0,08	2
Phoenix Contact	97 59 63 PC3	RC-20KS0,08-0,56	1241093	-	-	0,49	0,14	2
Phoenix Contact	97 59 63 PC3	RC-20KS0,08-0,56	1241093	-	-	0,59	0,25	2
Phoenix Contact	97 59 63 PC3	RC-20KS0,08-0,56	1241093	-	-	0,67	0,34	2
Phoenix Contact	97 59 63 PC3	RC-20KS0,08-0,56	1241093	-	-	0,72	0,50	2
Phoenix Contact	97 59 63 PC3	RC-59P2000	1603498	-	-	0,85	0,75	4
Phoenix Contact	97 59 63 PC3	RC-59P2000	1603498	-	-	0,88	1,00	4
Phoenix Contact	97 59 63 PC3	RC-59S2000	1603501	-	-	0,85	0,75	5
Phoenix Contact	97 59 63 PC3	RC-59S2000	1603501	-	-	0,88	1,00	5
Phoenix Contact	97 59 63 PC3	RC-5AP2000	1603505	-	-	0,85	1,50	4
Phoenix Contact	97 59 63 PC3	RC-5AP2000	1603505	-	-	1,05	2,50	4

Hersteller Manufacturer	Locator Knipex	Nummer 1 Contact No. 1	Nummer 2 Contact No. 2	Steckerserie (Gehäuse) Connector series (housing)	Crimpkontaktserie Crimp contact series	Einstellmaß Setting dim. [mm]	Querschnitt Cross-section [mm <sup>2</sup> ]	Locator- position
Phoenix Contact	97 59 63 PC3	RC-5AS2000	1603509	-	-	0,92	1,50	5
Phoenix Contact	97 59 63 PC3	RC-5AS2000	1603509	-	-	1,03	2,50	5
Phoenix Contact	97 59 63 PC3	RC-5CP2000	1603513	-	-	1,00	1,00	4
Phoenix Contact	97 59 63 PC3	RC-5CP2000	1603513	-	-	1,07	1,50	4
Phoenix Contact	97 59 63 PC3	RC-5CS2000	1603517	-	-	0,97	1,00	5
Phoenix Contact	97 59 63 PC3	RC-5CS2000	1603517	-	-	1,02	1,50	5
Phoenix Contact	97 59 63 PC3	RC-5NP2000	1603521	-	-	1,00	1,00	9
Phoenix Contact	97 59 63 PC3	RC-5NP2000	1603521	-	-	1,07	1,50	9
Phoenix Contact	97 59 63 PC3	RC-5PP2000	1603523	-	-	0,85	1,50	9
Phoenix Contact	97 59 63 PC3	RC-5PP2000	1603523	-	-	1,05	2,50	9
Phoenix Contact	97 59 63 PC3	RC-5QP2000	1603525	-	-	0,85	0,75	9
Phoenix Contact	97 59 63 PC3	RC-5QP2000	1603525	-	-	0,88	1,00	9
Phoenix Contact	97 59 63 PC3	RC-5SP2000	1603529	-	-	0,93	0,50	4
Phoenix Contact	97 59 63 PC3	RC-5SP2000	1603529	-	-	0,96	0,75	4
Phoenix Contact	97 59 63 PC3	RC-5SS2000	1603530	-	-	0,93	0,50	5
Phoenix Contact	97 59 63 PC3	RC-5SS2000	1603530	-	-	0,96	0,75	5
Phoenix Contact	97 59 63 PC3	ST-10KP0,06-1,00	1243215	-	-	0,57	AWG 22	8
Phoenix Contact	97 59 63 PC3	ST-10KP0,06-1,00	1243215	-	-	0,44	AWG 26	8